



## MARATHON MOTORS Fan Motor 1/3 HP 1140 rpm 60/50Hz, 39P318

Item **18JKK3811** Mfr. Model **056T11011001**

### Product Details

|                               |                                       |
|-------------------------------|---------------------------------------|
| Item Reference: <b>39P318</b> | Width (in): <b>8</b>                  |
| Brand: <b>MARATHON MOTORS</b> | Height (in): <b>8.75</b>              |
| Weight (lb): <b>22</b>        | Harmonization Code: <b>8501514040</b> |
| Length (in): <b>13.94</b>     | Country of Origin: <b>Mexico</b>      |

### Product Description

Condenser Fan Motor Three Phase Motor Design 3-Phase 1/3 HP Nameplate RPM 1 140 No of Speeds 1 Voltage 208-230/460V AC 1.80-1.80/0.90 Full Load Amps 56Z Frame Output Watts 250 W 60/50 Hz Usable @ 208V Yes Usable @ 200V No Motor Service Factor 1 Motor Thermal Protection Auto Ins. Class B Duty Cycle Continuous Max Ambient Temp 60 Degrees C Motor Shaft Rotation CW/CCW Motor Enclosure Design Open Air-Over Motor Mounting Type Rigid Base Motor Frame Material Steel