



SCHNEIDER ELECTRIC Manual Motor Starter Knob 20 to 25A 3P, 2MNK3

Item **04UNP29636** Mfr. Model **GV2P22**

Product Details

Item Reference: 2MNK3	Width (in): 1.9
Brand: SCHNEIDER ELECTRIC	Height (in): 3.8
Weight (lb): 0.82	Harmonization Code: 8536504000
Length (in): 3.7	Country of Origin: MULTIPLE

Product Description

Manual Motor Starter Operator Rotary Knob Enclosure NEMA Rating No Enclosure Overload Relay Amp Setting 20 to 25A Number of Poles 3 Description/Special Features Reliable Overload Protection Max Voltage 600V AC HP @ 3 Phase - 240V 7 1/2 hp HP @ 3 Phase - 480V 15 hp Height 3.5 in Width 1.75 in Depth 3.83 in HP @ 1 Phase - 120V 2 hp HP @ 1 Phase - 230V 3 hp HP @ 3 Phase - 208V 5 hp HP @ 3 Phase - 460-575V 15/20 HP @ 3 Phase - 575V 20 hp Standards CSA UL Pilot Light Yes