



## Fluke 177 True-RMS Digital Multimeter

Item **32FIK10715** Mfr. Model **FLUKE-177 EJKCT**

### Product Details

|                                                                   |                                         |
|-------------------------------------------------------------------|-----------------------------------------|
| Brand: <b>FLUKE</b>                                               | Current AC/DC: <b>10 A</b>              |
| Safety rating (IEC 61010) CAT IV: <b>600 V</b>                    | Voltage AC/DC: <b>1000 V</b>            |
| Safety rating (IEC 61010) CAT III: <b>1000 V</b>                  | AC bandwidth: <b>1 kHz</b>              |
| Operating temperature range: <b>-10° C, 50° C (14° F, 122° F)</b> | Basic dc accuracy: <b>0.09 %</b>        |
| Capacitance: <b>9999 µF</b>                                       | True-RMS readings: <b>AC</b>            |
| Frequency: <b>100 kHz</b>                                         | Part number: <b>1592888</b>             |
| Resistance: <b>50 MΩ</b>                                          | Country of Origin: <b>United States</b> |

### Product Description

The Fluke 177 True-RMS digital multimeter measures twice as fast as other multimeters; digital display with analog bar graph and backlight.

Safety rated CAT III 1000 V, CAT IV 600 V Measures AC and DC voltage to 1000 V True-RMS AC current and voltage plus frequency, capacitance, resistance, continuity and diode measurements